



## KLOWRA SPROUT MODULATION EFFECT

### Specific Functions

\*Press&Hold the Footswitch\*

#### • Tap Tempo

The Tap Tempo is a real-time setting (RATE) synchronized with the BPM by tapping the footswitch, Delivering the modulation effect a precise bite to the musical groove. After 5 seconds of inactivity, the LED will turn white, automatically exit the Tap Tempo.

#### • Ramp

Control the fading back and forth between the panel-set and the snap-set to create a dynamic effect. You can adjust the duration of the Ramp by modifying RampATK and RampRLS.

### Others

#### • Stereo Type

Dry/Wet Separation and True Stereo

#### • External Control

Use an external TS/TRS footswitch and expression pedal for multifunctional continuous control

#### • Bypass Mode

Buffer Bypass or True Bypass

#### • More Feature Selectable via Power Up Modes

Find more information at [www.klowra.com](http://www.klowra.com)

### Description of the LED Button

#### About LED Color

- White: The current footswitch specific function is Tap tempo
- Blue: Tap tempo is being triggered
- Orange: The current footswitch specific function is Ramp
- Violet: Ramp is being triggered

#### About Button Function

##### • Switching of Specific Functions: Press

##### • Save Snap-set: Press&Hold

Save snap-set by Press&Hold the LED button  
\*Save successfully indicated by LED blinking violet\*

##### • Adjustment of Hidden Parameters

Press&Hold, rotate the knob above the hidden parameters

\*Adjustment successfully indicated by LED blinking yellow\*

ADAPTER: 9V 250mA POLARITY:

Connect to 9V DC, center negative power supply, 250mA minimum.

**NOTE:** If the power supply is insufficient, it may cause malfunction. We recommend isolated power supply for your daily operation.

