

## OMNITRONIC PM-444Pi 4-channel DJ Mixer with Player & USB Interface

4-channel DJ mixer with Bluetooth, MP3 player and USB interface

Art. No.: 10006825

GTIN: 4026397704815



**List price: 296.31 €**

incl. 19% VAT.

### Features:

- 4 input channels with gain control, LED level meter, 3-band equalizer, cue button and channel fader
- 1 DJ microphone channel with level control, 2-band equalizer, on/off and talkover switch
- Built-in USB audio interface allows playback of digital audio files from a computer (PC and Mac)
- Prefader listening to input channels and the master output via adjustable headphones output, with cue mix/split function
- Crossfader with assignment switches
- Master channel with level and balance control
- 10-digit stereo LED level meter
- Adjustable monitor output
- 7 line and 2 phono inputs via RCA jacks
- Balanced XLR and RCA outputs
- Additional recording output
- (19") 48.3 cm rack installation 4 U
- Control via Bluetooth
- Bluetooth: operating range up to 10m in buildings
- Monochrome LCD display
- For application areas such as: Clubs/dancing school; installation; mobile djs / entertainer; restaurants, bars and hotels

### Logistic

EAN / GTIN: 4026397704815

Weight: 3,95 kg

Length: 0.49 m

Width: 0.22 m

Height: 0.14 m

### Technical specifications:

Power supply: 100-240 V AC, 50/60 Hz

Power consumption: Max. 10 W

|                        |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |
|------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Protection class:      | Protection class II                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |
| Power connection:      | Mains input via C8 (M) "figure 8" mounting version power supply cord with Euro plug (provided)                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |
| Cable construction:    | 2 x 0.75 mm² H05VVH2-F                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
| Frequency range:       | 20 - 20000 Hz                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |
| S/N ratio:             | >60 dB                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
| Impedance:             | Input: microphone 1 kOhm<br>Input: line 1 kOhm<br>Input: phono 1 kOhm                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |
| Gain:                  | Input: variable                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |
| Control:               | Bluetooth                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |
| Bluetooth:             | Version: 4.2 + EDR<br>Profiles: A2DP, AVRCP                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
| Bluetooth device name: | PM-444Pi                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    |
| Audio player:          | USB + Bluetooth                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |
| Range:                 | Bluetooth: up to 10m in buildings                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           |
| Carrier frequency:     | 2.4 GHz                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |
| Housing color:         | Black                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |
| Display type:          | Monochrome LCD display                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
| Display reading:       | Song title , play time remaining                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |
| Control elements:      | Crossfader selector switch, crossfader, source selector, power switch, Input sensitivity switch; audio player                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |
| Status LED:            | Power, CUE, master level meter, channel level meter                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |
| Connections:           | Input: microphone via 1 x 3-pin XLR/6.35mm jack (F) combination socket (mounting version)<br>Input: line via 5 x stereo RCA<br>Input: line/phono via 2 x stereo RCA<br>Output: master via 2 x 3-pin XLR<br>Output: master via 1 x stereo RCA<br>Output: booth via 1 x stereo RCA<br>Output: rec. via 1 x stereo RCA<br>Output: headphones via 1 x 6.3 mm jack socket (stereo) mounting version<br>Output: headphones via 1 x 3.5 mm jack (mono) mounting version                                                                                                                                                                                                                            |
| Channels:              | Input channel: 2 x stereo with line-phono switch via RCA, channel control via fader, 3-band tone control EQ -30dB to12dB at 80Hz/12kHz, gain control, CUE switch, crossfader selector switch, Input sensitivity switch, source selector<br><br>Input channel: 1 x stereo with line-line switch via RCA, channel control via fader, 3-band tone control EQ -30dB to12dB at 80Hz/12kHz, gain control, CUE switch, crossfader selector switch, source selector<br><br>Input channel: 1 x stereo with line-player switch via RCA or player, channel control via fader, 3-band tone control EQ -30dB to12dB at 80Hz/12kHz, gain control, CUE switch, crossfader selector switch, source selector |

Microphone channel: 1 x mono via Combination socket (XLR/jack), channel control via rotary dial, 2-band tone control EQ -30dB to12dB at 70Hz/13kHz, gain control, ON AIR switch, talkover switch

Master output: 1 x stereo via XLR or RCA, channel control via rotary dial, balancecontrol

Booth output: 1 x stereo via RCA, channel control via rotary dial

Rec. output: 1 x stereo via RCA

Headphones output: 1 x stereo via jack, channel control via rotary dial, cue mix function

|                          |                                                    |
|--------------------------|----------------------------------------------------|
| Music format:            | MP3, WAV; WAV                                      |
| USB port:                | USB 2.0, type B<br>Type A                          |
| Housing design:          | (19") 48.3 cm rack installation 4 U                |
| Mounting depth:          | 8.7 cm                                             |
| Dimensions:              | Width: 48.3 cm<br>Depth: 17.8 cm<br>Height: 8.9 cm |
| Weight:                  | 3.50 kg                                            |
| Available storage media: | USB devices max. 32GB (FAT 32)                     |

**Scope of delivery:**

- 1 x mixer
- 1 x power cord
- 1 x RCA cable
- 1 x USB cable
- 1 x user manual